

TAO-A.V-IDR9

TAO-A.V Option Switch Settings: 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill Rp 1000, 2000, 5000, 10000, 20000, 50000, 100000 7bills.
Coca-Cola Coupon – RED & GREEN 2bills.

TAO-V dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject Rp 1000 & 2000	ON											
★ Accept Rp 1000 & 2000	OFF											
★ Reject Rp 5000 & 10000		ON										
★ Accept Rp 5000 & 10000		OFF										
★ Reject Rp 20000 & 50000			ON									
★ Accept Rp 20000 & 50000			OFF									
★ Reject Rp 100000				ON								
★ Accept Rp 100000				OFF								
★ Accept Coca-Cola Coupon					ON							
★ Reject Coca-Cola Coupon					OFF							
★ Accept Green Coca-Cola Coupon	(Note A.)				ON							
★ Accept Red Coca-Cola Coupon	(Note A.)				OFF							
Pulse Mode	Other Mode											
★ Harness Disable	BA stops working when fishing				ON							
★ Harness Enable	Normal				OFF							
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / Rp 1000	MDB Mode coupon/ 4000				OFF	OFF						
5 pulses / Rp 1000	/ 5000				ON	OFF						
10 pulses / Rp 1000	/ 7000				OFF	ON						
20 pulses / Rp 1000	/ 127500				ON	ON						
★ Interface Timing Conversion	50ms LO / 50ms HI						OFF	OFF				
	60ms LO / 300ms HI						ON	OFF				
	30ms LO / 50ms HI						OFF	ON				
	150ms LO / 150ms HI						ON	ON				

★ Manufacture setting

◆ Note : (1)Please reset the bill acceptor after any changes on Dip switch.

(2)SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

Note A : Dip Switch 5 needs to set to ON position under the coupon mode.

Appendix

TAO-A.V-IDR9

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(ICT104U/ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse	ICT104U	ICT104V
BV1	1000	1000	1000	1000
BV2	2000	2000	2000	2000
BV3	5000	5000	5000	5000
BV4	10000	10000	10000	10000
BV5	20000	20000	20000	20000
BV6	50000	50000	50000	50000
BV7	100000	100000	100000	100000
BV8	Coupon(RED)	Coupon(RED)	Coupon(RED)	Coupon(RED)
BV9	Coupon(GREEN)	Coupon(GREEN)	Coupon(GREEN)	Coupon(GREEN)

TAO-V-IDR9

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting