

V7-RUR5

V7 Option Switch Settings: 1 (Pulse/ICT)

Supported bill Ruble 10, 50, 100, 500, 1000 5bills.

A7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Ruble 10	ON											
★	Accept Ruble 10	OFF											
★	Reject Ruble 50		ON										
★	Accept Ruble 50		OFF										
★	Reject Ruble 100			ON									
★	Accept Ruble 100			OFF									
★	Reject Ruble 500				ON								
★	Accept Ruble 500				OFF								
★	Reject Ruble 1000					ON							
★	Accept Ruble 1000					OFF							
★	Reserved						ON						
★	Reserved						OFF						
★	Harness Disable							ON					
★	Harness Engble							OFF					
★	Inhiblit Active High								ON				
★	Inhibit Active Low								OFF				
★	10 pulse / Ruble 10									OFF	OFF		
★	20 pulse / Ruble 10									ON	OFF		
★	50 pulse / Ruble 10									OFF	ON		
★	100 pulse / Ruble 10									ON	ON		
★	Pulse Speed	50ms on / 50ms off										OFF	OFF
		60ms on / 300ms off										ON	OFF
		30ms on / 50ms off										OFF	ON
		150ms on / 150ms off										ON	ON

◆ Factory configuration has all switches in the OFF position.

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW6 . SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7-RUR5

V7 Interface Settings: 2 (ICT)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
★	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
★	ICT Interface		OFF		
★	Reserved			ON	
★				OFF	
★					ON
★					OFF

★ Manufacture setting