

V77E-EGP4

V77E Option Switch Settings : 1(Pulse/RS232 A0/ccNet/ICT104U)

Supported bill EGP 5, 10, 20, 50 4bills.

V77E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject EGP 5	ON											
★ Accept EGP 5	OFF											
★ Reject EGP 10		ON										
★ Accept EGP 10		OFF										
★ Reject EGP 20			ON									
★ Accept EGP 20			OFF									
★ Reject EGP 50				ON								
★ Accept EGP 50				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / EGP 5									OFF	OFF		
2 pulses / EGP 5									ON	OFF		
5 pulses / EGP 5									OFF	ON		
20 pulses / EGP 5									ON	ON		
★ Pulse Speed		50ms on / 50ms off								OFF	OFF	
		60ms on / 300ms off								ON	OFF	
		30ms on / 50ms off								OFF	ON	
		150ms on / 150ms off								ON	ON	

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.
Note : (1) Default setting.

V77E-EGP4(Pulse/RS232 A0/ccNet/ICT104U)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Interface		ON	OFF	
★ RS232 A0 Interface		OFF	ON	
ccNet Interface		ON	ON	
ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(ccNet)

INTERFACE	SW1	SW2	SW3	SW4
19200 Baud rate	ON			
★ 9600 Baud rate	OFF			
Pulse Interface		ON	OFF	
★ RS232 A0 Interface		OFF	ON	
ccNet Interface		ON	ON	
ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(RS232 A0)

INTERFACE	SW1	SW2	SW3	SW4
Reserved	ON			
★ Reserved	OFF			
Pulse Interface		ON	OFF	
★ RS232 A0 Interface		OFF	ON	
ccNet Interface		ON	ON	
ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

RS232 A0 INFORMATION

Bill Type Data	
Code	Denomination
1	Reserved
2	EGP 5
3	EGP 10
4	EGP 20
5	EGP 50
6	Reserved
7	Reserved
8	Reserved

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
Reserved	ON			
★ Reserved	OFF			
Pulse Interface		ON	OFF	
RS232 A0 Interface		OFF	ON	
ccNet Interface		ON	ON	
★ ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	ccNet	ICT104U
BV1	EGP 5	EGP 5	EGP 5	EGP 5
BV2	EGP 10	EGP 10	EGP 10	EGP 10
BV3	EGP 20	EGP 20	EGP 20	EGP 20
BV4	EGP 50	EGP 50	EGP 50	EGP 50