

V77E-SDG5

V77E Option Switch Settings : 1(Pulse/Parallel A3/ICT104U/ MDB)

Supported bill SDG 1, 2, 5, 10, 20 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject SDG 1	ON											
★	Accept SDG 1	OFF											
	Reject SDG 2		ON										
★	Accept SDG 2		OFF										
★	Reject SDG 5			ON									
★	Accept SDG 5			OFF									
★	Reject SDG 10				ON								
★	Accept SDG 10				OFF								
★	Reject SDG 20					ON							
★	Accept SDG 20					OFF							
★	Reserved					ON							
★	Reserved					OFF							
★	Harness Disable							ON					
★	Harness Enable							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / SDG 1									OFF	OFF		
	2 pulses / SDG 1									ON	OFF		
	5 pulses / SDG 1									OFF	ON		
	10 pulses / SDG 1									ON	ON		
★	Pulse Speed	50ms on / 50ms off									OFF	OFF	
		60ms on / 300ms off									ON	OFF	
		30ms on / 50ms off									OFF	ON	
		150ms on / 150ms off									ON	ON	

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol .

V77E-SDG5(Pulse/Parallel A3/ICT104U/ MDB)

Interface Settings: 3(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Interface		ON	OFF	
	Parallel A3 Interface		OFF	OFF	
	MDB Interface		ON	ON	
	ICT Interface		OFF	ON	
★	Reserved			ON	
				OFF	

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	SDG 1	SDG 1
BV2	SDG 2	SDG 2
BV3	SDG 5	SDG 5
BV4	SDG 10	SDG 10
BV5	SDG 20	SDG 20
Interface Bill value	MDB	Parallel A3
BV1	SDG 1	SDG 1
BV2	SDG 2	SDG 2
BV3	SDG 5	SDG 5
BV4	SDG 10	SDG 10
BV5	SDG 20	

Interface Settings: 3(Parallel A3)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Interface		ON	OFF	
★	Parallel A3 Interface		OFF	OFF	
	MDB Interface		ON	ON	
	ICT Interface		OFF	ON	
★	Reserved			ON	
				OFF	

★ Manufacture setting

Interface Settings: 3(ICT)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Interface		ON	OFF	
	Parallel A3 Interface		OFF	OFF	
	MDB Interface		ON	ON	
★	ICT Interface		OFF	ON	
★	Reserved			ON	
				OFF	

★ Manufacture setting

Interface Settings: 3(MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Interface		ON	OFF	
	Parallel A3 Interface		OFF	OFF	
★	MDB Interface		ON	ON	
	ICT Interface		OFF	ON	
★	Reserved			ON	
				OFF	

★ Manufacture setting