

V7E/LX7-USD6

V7E/LX7 Option Switch Settings: 1(Pulse/ICT002U/NISR)

Supported bill USD 1, 5, 10, 20, 50, 100 6 bills.

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject USD 1	ON											
★ Accept USD 1	OFF											
Reject USD 5		ON										
★ Accept USD 5		OFF										
Reject USD 10			ON									
★ Accept USD 10			OFF									
Reject USD 20				ON								
★ Accept USD 20				OFF								
Reject USD 50 & 100					ON							
★ Accept USD 50 & 100					OFF							
Reserved					ON							
★ Reserved					OFF							
Harness Disable						ON						
★ Harness Enable						OFF						
Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / USD 1								OFF	OFF			
2 pulses / USD 1								ON	OFF			
4 pulses / USD 1								OFF	ON			
20 pulses / USD 1								ON	ON			
★ Pulse Speed		50ms LO / 50ms HI								OFF	OFF	
		60ms LO / 300ms HI								ON	OFF	
		30ms LO / 50ms HI								OFF	ON	
		150ms LO / 150ms HI								ON	ON	

★ Manufacture setting

Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

V7E/LX7-USD6(Pulse/ICT002U/NISR)

DIP SWITCHES SETTING: 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
AUTO (NISR/Pulse)		OFF	OFF	
NISR Mode		ON	ON	
ICT002U Mode		OFF	ON	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING: 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ AUTO (NISR/Pulse)		OFF	OFF	
NISR Mode		ON	ON	
ICT002U Mode		OFF	ON	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING: 2(NISR)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
AUTO (NISR/Pulse)		OFF	OFF	
NISR Mode		ON	ON	
★ ICT002U Mode		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT002U	NISR
BV1	USD 1	USD 1	USD 1
BV2			
BV3	USD 5	USD 5	USD 5
BV4	USD 10	USD 10	USD 10
BV5	USD 20	USD 20	USD 20
BV6	USD 50	USD 50	USD 50
BV7	USD 100	USD 100	USD 100