



IRR4

L77 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill Rials 1000, 2000, 5000, 10000, 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / Rials 1000	OFF	OFF	OFF								
	2 Pulse / Rials 1000	OFF	OFF	ON								
	3 Pulse / Rials 1000	OFF	ON	OFF								
	4 Pulse / Rials 1000	OFF	ON	ON								
	5 Pulse / Rials 1000	ON	OFF	OFF								
	10 Pulse / Rials 1000	ON	OFF	ON								
	20 Pulse / Rials 1000	ON	ON	OFF								
	100 Pulse / Rials 1000	ON	ON	ON								
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON							
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF							
	Inhibit level Active Low				ON							
★	Inhibit level Active High				OFF							
★	Accept Rials 1000						ON					
	Reject Rials 1000						OFF					
★	Accept Rials 2000							ON				
	Reject Rials 2000							OFF				
★	Accept Rials 5000								ON			
	Reject Rials 5000								OFF			
★	Accept Rials 10000									ON		
	Reject Rials 10000									OFF		
	Reserved										ON	
★	Reserved										OFF	

★ Manufacture setting

Note:(1)Please reset the bill acceptor after any changes on Dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal HIGH	ON			
	Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	ICT Protocol Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting