

# L77F&PL77-THB5

## L77F&PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT002U)

Supported bill ₪ 20, 50, 100, 500, 1000

5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / ₪ 10	OFF	OFF	OFF							
2 Pulse / ₪ 10	OFF	OFF	ON							
3 Pulse / ₪ 10	OFF	ON	OFF							
4 Pulse / ₪ 10	OFF	ON	ON							
5 Pulse / ₪ 10	ON	OFF	OFF							
10 Pulse / ₪ 10	ON	OFF	ON							
20 Pulse / ₪ 10	ON	ON	OFF							
100 Pulse / ₪ 10	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept ₪ 20 & 50				ON						
★ Reject ₪ 20 & 50				OFF						
★ Accept ₪ 100				ON						
★ Reject ₪ 100				OFF						
★ Accept ₪ 500				ON						
★ Reject ₪ 500				OFF						
★ Accept ₪ 1000				ON						
★ Reject ₪ 1000				OFF						
★ High Security				ON						
★ High Acceptance <small>(Note.3)</small>				OFF						

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

(3)High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

## DIP SWITCHES SETTING : 2 Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
ICT002U Mode		OFF		
Reserved			ON	
★ Reserved			OFF	
Reserved			ON	
★ Reserved			OFF	

Interface Bill value	ICT	Pulse
BV1	₪ 20	₪ 20
BV2	₪ 50	₪ 50
BV3	₪ 100	₪ 100
BV4	₪ 500	₪ 500
BV5	₪ 1000	₪ 1000

★ Manufacture setting