

## **BGL5**

## **L83 DIP SWITCHES SETTING: 1(Pulse/Parallel A4)**

## Supported bill BGL 5, 10, 20, 50, 100 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
*	1 Pulse / BGL 5	OFF	OFF	OFF							
	2 Pulses / BGL 5	OFF	OFF	ON							
	3 Pulses / BGL 5	OFF	ON	OFF							
	4 Pulses / BGL 5	OFF	ON	ON							
	5 Pulses / BGL 5	ON	OFF	OFF							
	10 Pulses / BGL 5	ON	OFF	ON							
	20 Pulses / BGL 5	ON	ON	OFF							
	100 Pulses / BGL 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
*	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
*	Inhibit level Active High					OFF					
*	Accept BGL 5						ON				
	Reject BGL 5						OFF				
*	Accept BGL 10							ON			
	Reject BGL 10							OFF			
*	Accept BGL 20								ON		
	Reject BGL 20								OFF		
*	Accept BGL 50	ON								ON	
	Reject BGL 50									OFF	
*	Accept BGL 100										ON
	Reject BGL 100										OFF

## **DIP SWITCHES SETTING: 2**

	Reserved		ON	ON	
*	Pulse Mode		ON	OFF	
	Parallel A4 without Escrow Mode		OFF	ON	
	Parallel A4 without Escrow Mode		OFF	OFF	
	Credit-Pulse Normal LOW	OFF			
*	Credit-Pulse Normal HIGH	ON			
	FUNCTION	SW1	SW2	SW3	SW4

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.