

NE77-RON4

NE77 DIP SWITCHES SETTING : (Pulse/ICT106U)

Supported bill RON 1, 5, 10, 50 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / RON 1	OFF	OFF								
	2 Pulse / RON 1	OFF	ON								
	5 Pulse / RON 1	ON	OFF								
	10 Pulse / RON 1	ON	ON								
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>			ON							
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>			OFF							
★	Inhibit level Active Low				ON						
	Inhibit level Active High				OFF						
★	Accept RON 1					ON					
	Reject RON 1					OFF					
★	Accept RON 5 & 10						ON				
	Reject RON 5 & 10						OFF				
★	Accept RON 50							ON			
	Reject RON 50							OFF			
★	Pulse Normal High								ON		
	Pulse Normal Low								OFF		
★	Pulse Mode									ON	
	ICT106U Mode									OFF	
★	Manufacture Default										ON
	System Default										OFF

(★) Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT106U
BV1	RON 1	RON 1
BV2	RON 5	RON 5
BV3	RON 10	RON 10
BV4	RON 50	RON 50