

NK77-PHP6

NK77 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill PHP 20, 50, 100, 200, 500, 1000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / PHP 10	OFF	OFF								
	5 Pulses / PHP 10	OFF	ON								
	10 Pulses / PHP 10	ON	OFF								
	20 Pulses / PHP 10	ON	ON								
	Fast output Pulse Lo= 50ms Hi=100ms			ON							
★	Slow output Pulse Lo= 50ms Hi=300ms			OFF							
★	Inhibit level Active Low				ON						
	Inhibit level Active High				OFF						
★	Accept PHP 20 & 50					ON					
	Reject PHP 20 & 50					OFF					
★	Accept PHP 100 & 200						ON				
	Reject PHP 100 & 200						OFF				
★	Accept PHP 500 & 1000							ON			
	Reject PHP 500 & 1000							OFF			
★	Pulse Normal High								ON		
	Pulse Normal Low								OFF		
★	Pulse Mode									ON	
	ICT104U Mode									OFF	
★	Reserved										ON
	Reserved										OFF

(★) Manufacture setting

Note : Please reset the bill acceptor
after set the dip switch.

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	PHP 20	PHP 20
BV2	PHP 50	PHP 50
BV3	PHP 100	PHP 100
BV4	PHP 500	PHP 200
BV5	PHP 1000	PHP 500
BV6	PHP 200	PHP 1000