

XBA mini-KRW4+USD4

XBA mini Option Switch Settings: 1(ICT104U)

Supported bill KRW 1000, 5000, 10000, 50000 4bills
 USD 10, 20, 50, 100 4bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
	Reject KRW 1000 & 5000	ON							
★	Accept KRW 1000 & 5000	OFF							
	Reject KRW 10000 & 50000		ON						
★	Accept KRW 10000 & 50000		OFF						
	Reject USD 10 & 20			ON					
★	Accept USD 10 & 20			OFF					
	Reject USD 50				ON				
★	Accept USD 50				OFF				
	Reject USD 100					ON			
★	Accept USD 100					OFF			
	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON		
★	EnableBill Reject 4 Times BA Stop By 30 Sec						OFF		
	Stack Banknote when Power-up							ON	
★	Reject Banknote when Power-up							OFF	
★	Reserved								ON
	Reserved								OFF

Currency Assign Data

Interface Bill value	ICT104U		ICT104U
BV1	KRW 1000	BV5	USD 10
BV2	KRW 5000	BV6	USD 20
BV3	KRW 10000	BV7	USD 50
BV4	KRW 50000	BV8	USD 100

★ Manufacture setting

Note :1. After setting dip switch of the credit pulses,
 you should reset the bill acceptor again.
 2. Calibration card is needed.