

A6 Option Switch Settings:(RS232)**Supported bill US\$ 1, 5 2bills.**

A6 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
	Reject US\$ 1	ON							
★	Accept US\$ 1	OFF							
	Reject US\$ 5		ON						
★	Accept US\$ 5		OFF						
★	Reserved			OFF	OFF				
	Reserved			ON	OFF				
	Reserved			OFF	ON				
	Reserved			ON	ON				
★	Reserved					OFF	OFF		
	Reserved					ON	OFF		
	Reserved					OFF	ON		
	Reserved					ON	ON		
	Reserved							ON	
★	Reserved							OFF	
	Reserved								ON
★	Reserved								OFF

◆ Factory configuration has all switches in the OFF position.

Note : Reset the bill acceptor after setting the dip switch.

