

A7/V7 Option Switch Settings

Supported bill US\$ 1(95, 99), 5(99, 03), 10(99, 04), 20(96, 99, 04),
50(96, 04), 100(96, 99, 01) 6bills.


A7/V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
Reject US\$ 1	ON											
Accept US\$ 1	OFF											
Reject US\$ 5		ON										
Accept US\$ 5		OFF										
Reject US\$ 10			ON									
Accept US\$ 10			OFF									
Reject US\$ 20				ON								
Accept US\$ 20				OFF								
Reject US\$ 50 & 100					ON							
Accept US\$ 50 & 100					OFF							
High Acceptance						ON						
High Security						OFF						
Harness disable							ON					
Harness enable							OFF					
Inhibit Active High								ON				
Inhibit Active Low								OFF				
1 pulse / one dollar									OFF	OFF		
2 pulse / one dollar									ON	OFF		
4 pulse / one dollar									OFF	ON		
20 pulse / one dollar									ON	ON		
Pulse Speed	50ms on / 50ms off										OFF	OFF
	60ms on / 300ms off										ON	OFF
	30ms on / 50ms off										OFF	ON
	150ms on / 150ms off										ON	ON

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.



核准: 孫朋文

05.1.27

A7/V7 Option Switch Settings

Supported bill US\$ 1(95, 99, 01, 03), 5(99, 01, 03), 10(99, 01, 04),
20(96, 99, 04), 50(96, 04), 100(96, 99, 01, 03) 6bills.

A7/V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
Reject US\$ 1	ON											
Accept US\$ 1	OFF											
Reject US\$ 5		ON										
Accept US\$ 5		OFF										
Reject US\$ 10			ON									
Accept US\$ 10			OFF									
Reject US\$ 20				ON								
Accept US\$ 20				OFF								
Reject US\$ 50 & 100					ON							
Accept US\$ 50 & 100					OFF							
High Acceptance						ON						
High Security						OFF						
Harness disable							ON					
Harness enable							OFF					
Inhibit Active High								ON				
Inhibit Active Low								OFF				
1 pulse / one dollar									OFF	OFF		
2 pulse / one dollar									ON	OFF		
4 pulse / one dollar									OFF	ON		
20 pulse / one dollar									ON	ON		
Pulse Speed	50ms on / 50ms off										OFF	OFF
	60ms on / 300ms off										ON	OFF
	30ms on / 50ms off										OFF	ON
	150ms on / 150ms off										ON	ON

- ◆ Factory configuration has all switches in the OFF position.
- Note : (1) Reset the bill acceptor after setting the dip switch.
- (2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

