

# A7/V7-NZD3

## A7/V7 Option Switch Settings

Supported bill NZ\$ 5, 10, 20 3bills.

A7/V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject NZ\$ 5	ON											
★ Accept NZ\$ 5	OFF											
★ Reject NZ\$ 10		ON										
★ Accept NZ\$ 10		OFF										
★ Reject NZ\$ 20			ON									
★ Accept NZ\$ 20			OFF									
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / NZ\$ 5									OFF	OFF		
★ 5 pulse / NZ\$ 5									ON	OFF		
★ 10 pulse / NZ\$ 5									OFF	ON		
★ 25 pulse / NZ\$ 5									ON	ON		
★ Pulse Speed	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

# A7/V7-NZD3

## A7/V7 Interface Settings: 2 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
★ RS232 Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

## A7/V7 Interface Settings: 3 (RS232)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ Pulse Mode		ON		
★ RS232 Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	NZ\$ 5	NZ\$ 5
BV2	NZ\$ 10	NZ\$ 10
BV3	NZ\$ 20	NZ\$ 20

## V7 Interface Settings: 2 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
★ MDB Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

## V7 Interface Settings: 3 (MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★ Pulse Mode		ON		
★ MDB Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	NZ\$ 5	NZ\$ 5
BV2	NZ\$ 10	NZ\$ 10
BV3	NZ\$ 20	NZ\$ 20