



## BOB5

### L70/P5 DIP SWITCHES SETTING : 1(Pulse/RS232 A0)

Supported bill \$b 10, 20, 50, 100, 200 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / \$b 10	OFF	OFF	OFF							
	2 Pulses / \$b 10	OFF	OFF	ON							
	3 Pulses / \$b 10	OFF	ON	OFF							
	4 Pulses / \$b 10	OFF	ON	ON							
	5 Pulses / \$b 10	ON	OFF	OFF							
	10 Pulses / \$b 10	ON	OFF	ON							
	20 Pulses / \$b 10	ON	ON	OFF							
	100 Pulses / \$b 10	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept \$b 10					ON					
	Reject \$b 10					OFF					
★	Accept \$b 20						ON				
	Reject \$b 20						OFF				
★	Accept \$b 50							ON			
	Reject \$b 50							OFF			
★	Accept \$b 100								ON		
	Reject \$b 100								OFF		
★	Accept \$b 200									ON	
	Reject \$b 200									OFF	

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

## L70-BOB5(Pulse/RS232 A0)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	RS232 A0 Protocol Mode		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	RS232 A0 Protocol Mode		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting