

L70-BRA6

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill R\$ 2, 5, 10, 20, 50, 100

6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / R\$ 1	OFF	OFF								
2 Pulse / R\$ 1	OFF	ON								
4 Pulse / R\$ 1	ON	OFF								
10 Pulse / R\$ 1	ON	ON								
★ Output Pulse <small>Lo= 50ms Hi=100ms</small>			OFF	OFF						
Output Pulse <small>Lo=150ms Hi=100ms</small>			OFF	ON						
Output Pulse <small>Lo= 20ms Hi=100ms</small>			ON	OFF						
Output Pulse <small>Lo= 30ms Hi=150ms</small>			ON	ON						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept R\$ 2						ON				
Reject R\$ 2						OFF				
★ Accept R\$ 5							ON			
Reject R\$ 5							OFF			
★ Accept R\$ 10								ON		
Reject R\$ 10								OFF		
★ Accept R\$ 20									ON	
Reject R\$ 20									OFF	
★ Accept R\$ 50 & 100										ON
Reject R\$ 50 & 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Credit - Pulse Normal High	ON			
Credit - Pulse Normal Low	OFF			
★ Pulse Mode		ON		
ICT104U Mode		OFF		
★ Reserved			ON	
			OFF	
★				ON
				OFF

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	1	1
BV2	2	2
BV3	5	5
BV4	10	10
BV5	20	20
BV6	50	50
BV7	100	100