

L70+/L70F-BRL5

L70+/L70F DIP SWITCHES SETTING : 1(ICT104U/Pulse)

Supported bill R\$ 2, 5, 10, 20
 Coupon 5, 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / R\$ 1	OFF	OFF								
	2 Pulses / R\$ 1	OFF	ON								
	4 Pulses / R\$ 1	ON	OFF								
	10 Pulses / R\$ 1	ON	ON								
★	Output Pulse <small>Lo= 50ms Hi=100ms</small>			OFF	OFF						
	Output Pulse <small>Lo=150ms Hi=100ms</small>			OFF	ON						
	Output Pulse <small>Lo= 20ms Hi=100ms</small>			ON	OFF						
	Output Pulse <small>Lo= 30ms Hi=150ms</small>			ON	ON						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept R\$ 2						ON				
	Reject R\$ 2						OFF				
★	Accept R\$ 5							ON			
	Reject R\$ 5							OFF			
★	Accept R\$ 10								ON		
	Reject R\$ 10								OFF		
★	Accept R\$ 20									ON	
	Reject R\$ 20									OFF	
★	Accept R\$ Coupon 5										ON
	Reject R\$ Coupon 5										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Mode		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

Interface Bill value	ICT104U	Pulse
BV1	R\$ 2	R\$ 2
BV2	R\$ 5	R\$ 5
BV3	R\$ 10	R\$ 10
BV4	R\$ 20	R\$ 20
BV5	Coupon 5	Coupon 5