



COP6

L70/P5 DIP SWITCHES SETTING : 1(ICT/Pulse)

Supported bill Col\$ 1000, 2000, 5000, 10000, 20000, 50000
6 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Col\$ 1000	OFF	OFF	OFF							
2 Pulse / Col\$ 1000	OFF	OFF	ON							
3 Pulse / Col\$ 1000	OFF	ON	OFF							
4 Pulse / Col\$ 1000	OFF	ON	ON							
5 Pulse / Col\$ 1000	ON	OFF	OFF							
10 Pulse / Col\$ 1000	ON	OFF	ON							
20 Pulse / Col\$ 1000	ON	ON	OFF							
100 Pulse / Col\$ 1000	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept Col\$ 1000						ON				
Reject Col\$ 1000						OFF				
★ Accept Col\$ 2000							ON			
Reject Col\$ 2000							OFF			
★ Accept Col\$ 5000 & 10000								ON		
Reject Col\$ 5000 & 10000								OFF		
★ Accept Col\$ 20000									ON	
Reject Col\$ 20000									OFF	
★ Accept Col\$ 50000										ON
Reject Col\$ 50000										OFF

★ Manufacture setting

Note: (1)Please reset the bill acceptor after any changes on Dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Credit - Pulse Normal High	ON			
Credit - Pulse Normal Low	OFF			
★ Pulse Mode		ON		
ICT Mode		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF