



EUR2

L70/P5 DIP SWITCHES SETTING : 1(Pulse/RS232 A0)

Supported bill Euro 5, 10

2bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / Euro 5	OFF	OFF	OFF								
	2 Pulses / Euro 5	OFF	OFF	ON								
	3 Pulses / Euro 5	OFF	ON	OFF								
	4 Pulses / Euro 5	OFF	ON	ON								
	5 Pulses / Euro 5	ON	OFF	OFF								
	10 Pulses / Euro 5	ON	OFF	ON								
	20 Pulses / Euro 5	ON	ON	OFF								
	100 Pulses / Euro 5	ON	ON	ON								
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>											ON
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>											OFF
	Inhibit level Active Low				ON							
★	Inhibit level Active High				OFF							
★	Accept Euro 5				ON							
	Reject Euro 5				OFF							
★	Accept Euro 10				ON							
	Reject Euro 10				OFF							
	Reserved				ON							
★	Reserved				OFF							
	Reserved				ON							
★	Reserved				OFF							
	Reserved				ON							
★	Reserved				OFF							

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.
 (2) Dip switches 1 to 5 are only used for pulse protocol.

L70-EUR2P5(Pulse/RS232 A0)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	RS232 A0 Interface Mode		OFF		
★	Reserved			ON	
				OFF	
★					
★					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	RS232 A0 Interface Mode		OFF		
★	Reserved			ON	
				OFF	
★					
★					OFF

★ Manufacture setting