

KHR3

L70/P5 DIP SWITCHES SETTING : 1(ICT/Pulse)

Supported bill Riel 100, 500, 1000

3 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Riel 100	OFF	OFF	OFF							
	2 Pulse / Riel 100	OFF	OFF	ON							
	3 Pulse / Riel 100	OFF	ON	OFF							
	4 Pulse / Riel 100	OFF	ON	ON							
	5 Pulse / Riel 100	ON	OFF	OFF							
	10 Pulse / Riel 100	ON	OFF	ON							
	20 Pulse / Riel 100	ON	ON	OFF							
	100 Pulse / Riel 100	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>										
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept Riel 100				ON						
	Reject Riel 100				OFF						
★	Accept Riel 500				ON						
	Reject Riel 500				OFF						
★	Accept Riel 1000				ON						
	Reject Riel 1000				OFF						
	Reserved				ON						
★	Reserved				OFF						
	Reserved				ON						
★	Reserved				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Mode		OFF		
★	Reserved			ON	
				OFF	
				ON	
★				OFF	

Currency Assign Data

Interface Bill value	Pulse	ICT
BV1	100	100
BV2	500	500
BV3	1000	1000