

KHR6

L70/P5 DIP SWITCHES SETTING : 1(ICT/Pulse)

Supported bill Riel 100, 500, 1000, 2000, 5000, 10000 6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / Riel 100	OFF	OFF	OFF								
	2 Pulse / Riel 100	OFF	OFF	ON								
	3 Pulse / Riel 100	OFF	ON	OFF								
	4 Pulse / Riel 100	OFF	ON	ON								
	5 Pulse / Riel 100	ON	OFF	OFF								
	10 Pulse / Riel 100	ON	OFF	ON								
	20 Pulse / Riel 100	ON	ON	OFF								
	100 Pulse / Riel 100	ON	ON	ON								
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>											ON
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF							
★	Inhibit level Active High					ON						
	Inhibit level Active Low					OFF						
★	Accept Riel 100						ON					
	Reject Riel 100						OFF					
★	Accept Riel 500 & 1000							ON				
	Reject Riel 500 & 1000							OFF				
★	Accept Riel 2000								ON			
	Reject Riel 2000								OFF			
★	Accept Riel 5000									ON		
	Reject Riel 5000									OFF		
★	Accept Riel 10000										ON	
	Reject Riel 10000										OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Mode		OFF		
★	Reserved			ON	
				OFF	
				ON	
★				OFF	

Currency Assign Data

Interface Bill value	Pulse	ICT
BV1	100	100
BV2	500	500
BV3	1000	1000
BV4	2000	2000
BV5	5000	5000
BV6	10000	10000