

## L70-TWD4

### L70 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill NTD 100, 200, 500, 1000 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / NTD 100	OFF	OFF	OFF							
2 Pulse / NTD 100	OFF	OFF	ON							
3 Pulse / NTD 100	OFF	ON	OFF							
4 Pulse / NTD 100	OFF	ON	ON							
5 Pulse / NTD 100	ON	OFF	OFF							
10 Pulse / NTD 100	ON	OFF	ON							
20 Pulse / NTD 100	ON	ON	OFF							
100 Pulse / NTD 100	ON	ON	ON							
Fast output Pulse Lo=50ms Hi=100ms				ON						
★ Slow output Pulse Lo=50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept NTD 100						ON				
Reject NTD 100						OFF				
★ Accept NTD 200							ON			
Reject NTD 200							OFF			
★ Accept NTD 500								ON		
Reject NTD 500								OFF		
★ Accept NTD 1000									ON	
Reject NTD 1000									OFF	
Reserved										ON
★ Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## L70-TWD4/P5(Pulse/ICT104U)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ICT104U Protocol		OFF		
Reserved			ON	
★ Disable Inverse Mode			OFF	ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Protocol		ON		
★ ICT104U Protocol		OFF		
Reserved			ON	
★ Disable Inverse Mode			OFF	ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	NTD 100	NTD 100
BV2	NTD 200	NTD 200
BV3	NTD 500	NTD 500
BV4	NTD 1000	NTD 1000