

L70+/L70F-COP6

L70+/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/RS232 A0/Parallel A1)

Supported bill COP 2000, 5000, 10000, 20000, 50000, 100000 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / COP 1000	OFF	OFF	OFF							
2 Pulses / COP 1000	OFF	OFF	ON							
3 Pulses / COP 1000	OFF	ON	OFF							
4 Pulses / COP 1000	OFF	ON	ON							
5 Pulses / COP 1000	ON	OFF	OFF							
10 Pulses / COP 1000	ON	OFF	ON							
20 Pulses / COP 1000	ON	ON	OFF							
100 Pulses / COP 1000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms										
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept COP 2000						ON				
Reject COP 2000						OFF				
★ Accept COP 5000							ON			
Reject COP 5000							OFF			
★ Accept COP 10000								ON		
Reject COP 10000								OFF		
★ Accept COP 20000									ON	
Reject COP 20000									OFF	
★ Accept COP 50000 & 100000										ON
Reject COP 50000 & 100000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70+/L70F-COP6/P5(Pulse/RS232 A0/Parallel A1)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
Parallel A1 Mode		OFF	ON	
RS232 A0 Mode		OFF	OFF	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel A1)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ Parallel A1 Mode		OFF	ON	
RS232 A0 Mode		OFF	OFF	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
Parallel A1 Mode		OFF	ON	
★ RS232 A0 Mode		OFF	OFF	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	RS232 A0	Pulse	Parallel A1
BV1			
BV2	COP 2000	COP 2000	COP 2000
BV3	COP 5000	COP 5000	COP 5000
BV4	COP 10000	COP 10000	COP 10000
BV5	COP 20000	COP 20000	COP 20000
BV6	COP 50000	COP 50000	COP 50000
BV7	COP 100000	COP 100000	COP 100000

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	COP 1000
2	COP 2000
3	COP 5000
4	COP 10000
5	COP 20000
6	COP 50000
7	COP 100000
8	Reserved
9	Reserved