

## P77-CHF4

### P77/P5 DIP SWITCHES SETTING : 1(Pulse/M.D.B)

Supported bill Sw F 10, 20, 50, 100 4bills

| FUNCTION                                    | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ 1 Pulse / Sw F 10                         | OFF | OFF | OFF |     |     |     |     |     |     |      |
| 2 Pulse / Sw F 10                           | OFF | OFF | ON  |     |     |     |     |     |     |      |
| 3 Pulse / Sw F 10                           | OFF | ON  | OFF |     |     |     |     |     |     |      |
| 4 Pulse / Sw F 10                           | OFF | ON  | ON  |     |     |     |     |     |     |      |
| 5 Pulse / Sw F 10                           | ON  | OFF | OFF |     |     |     |     |     |     |      |
| 10 Pulse / Sw F 10                          | ON  | OFF | ON  |     |     |     |     |     |     |      |
| 20 Pulse / Sw F 10                          | ON  | ON  | OFF |     |     |     |     |     |     |      |
| 100 Pulse / Sw F 10                         | ON  | ON  | ON  |     |     |     |     |     |     |      |
| Fast output Pulse<br>Lo= 50ms<br>Hi=100ms   |     |     |     | ON  |     |     |     |     |     |      |
| ★ Slow output Pulse<br>Lo= 50ms<br>Hi=300ms |     |     |     | OFF |     |     |     |     |     |      |
| Inhibit level Active Low                    |     |     |     |     | ON  |     |     |     |     |      |
| ★ Inhibit level Active High                 |     |     |     |     | OFF |     |     |     |     |      |
| ★ Accept Sw F 10                            |     |     |     |     |     | ON  |     |     |     |      |
| Reject Sw F 10                              |     |     |     |     |     | OFF |     |     |     |      |
| ★ Accept Sw F 20                            |     |     |     |     |     |     | ON  |     |     |      |
| Reject Sw F 20                              |     |     |     |     |     |     | OFF |     |     |      |
| ★ Accept Sw F 50                            |     |     |     |     |     |     |     | ON  |     |      |
| Reject Sw F 50                              |     |     |     |     |     |     |     | OFF |     |      |
| ★ Accept Sw F 100                           |     |     |     |     |     |     |     |     | ON  |      |
| Reject Sw F 100                             |     |     |     |     |     |     |     |     | OFF |      |
| ★ Reserved                                  |     |     |     |     |     |     |     |     |     | ON   |
| Reserved                                    |     |     |     |     |     |     |     |     |     | OFF  |

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

## P77-CHF4(Pulse/MDB)

### DIP SWITCHES SETTING : 2(Pulse)

| FUNCTION            | SW1 | SW2 | SW3 | SW4 |
|---------------------|-----|-----|-----|-----|
| ★ Pulse Normal High | ON  |     |     |     |
| Pulse Normal Low    | OFF |     |     |     |
| ★ Pulse Mode        |     | ON  |     |     |
| MDB Interface       |     | OFF |     |     |
| Harness Disable     |     |     | ON  |     |
| ★ Harness Enable    |     |     | OFF |     |
| Reserved            |     |     |     | ON  |
| ★                   |     |     |     | OFF |

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

### DIP SWITCHES SETTING : 2(MDB)

| FUNCTION  | SW1 | SW2 | SW3 | SW4 |
|---|-----|-----|-----|-----|
| ★ Scaling Factor (SF) = 100<br>Decimal Point Position (DPP) = 2 | ON  |     |     |     |
| Scaling Factor (SF) = 1<br>Decimal Point Position (DPP) = 0     | OFF |     |     |     |
| Pulse Mode  |     | ON  |     |     |
| ★ MDB Interface   |     | OFF |     |     |
| Reserved  |     |     | ON  |     |
| ★   |     |     | OFF |     |
| Reserved  |     |     |     | ON  |
| ★   |     |     |     | OFF |

★ Manufacture setting

### Currency Assign Data

| Interface<br>Bill value | MDB      | Pulse    |
|-------------------------|----------|----------|
| BV1                     | Sw F 10  | Sw F 10  |
| BV2                     | Sw F 20  | Sw F 20  |
| BV3                     | Sw F 50  | Sw F 50  |
| BV4                     | Sw F 100 | Sw F 100 |