

## P77-HRK5

### P77/P5 DIP SWITCHES SETTING : 1(Pulse/M.D.B)

Supported bill Kuna 10, 20, 50, 100, 200 5 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Kuna 10	OFF	OFF	OFF							
2 Pulse / Kuna 10	OFF	OFF	ON							
3 Pulse / Kuna 10	OFF	ON	OFF							
4 pulse / Kuna 10	OFF	ON	ON							
5 Pulse / Kuna 10	ON	OFF	OFF							
10 Pulse / Kuna 10	ON	OFF	ON							
20 Pulse / Kuna 10	ON	ON	OFF							
100 Pulse / Kuna 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Kuna 10						ON				
Reject Kuna 10						OFF				
★ Accept Kuna 20							ON			
Reject Kuna 20							OFF			
★ Accept Kuna 50								ON		
Reject Kuna 50								OFF		
★ Accept Kuna 100									ON	
Reject Kuna 100									OFF	
★ Accept Kuna 200										ON
Reject Kuna 200										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## P77-HRK5/P5(Pulse/M.D.B)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
M.D.B Interface		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
★ Reserved				ON
				OFF

★ Manufacture setting.

### DIP SWITCHES SETTING : 2(M.D.B)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON		
★ M.D.B Interface		OFF		
★ Reserved			ON	
			OFF	
★ Reserved				ON
				OFF

★ Manufacture setting.

### Currency Assign Data

Interface Bill value	MDB	Pulse
BV1	10	10
BV2	20	20
BV3	50	50
BV4	100	100
BV5	200	200