



**JPY4**

**P77/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)**

Supported bill ¥ 1000, 2000, 5000, 10000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / ¥ 1000	OFF	OFF	OFF							
	2 Pulse / ¥ 1000	OFF	OFF	ON							
	3 Pulse / ¥ 1000	OFF	ON	OFF							
	4 Pulse / ¥ 1000	OFF	ON	ON							
	5 Pulse / ¥ 1000	ON	OFF	OFF							
	10 Pulse / ¥ 1000	ON	OFF	ON							
	20 Pulse / ¥ 1000	ON	ON	OFF							
	100 Pulse / ¥ 1000	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept ¥ 1000						ON				
	Reject ¥ 1000						OFF				
★	Accept ¥ 2000							ON			
	Reject ¥ 2000							OFF			
★	Accept ¥ 5000								ON		
	Reject ¥ 5000								OFF		
★	Accept ¥ 10000									ON	
	Reject ¥ 10000									OFF	
★	Accept new & old version bill										ON
	Reject old version bill										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

**DIP SWITCHES SETTING : 2**

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
★	Manufacture Default				ON
	System Default				OFF

★ Manufacture setting