

PLN5

P77/P5 DIP SWITCHES SETTING : 1(Pulse/MDB)

Supported bill zloty 10, 20, 50, 100, 200 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / zloty 10	OFF	OFF	OFF							
2 Pulse / zloty 10	OFF	OFF	ON							
3 Pulse / zloty 10	OFF	ON	OFF							
4 Pulse / zloty 10	OFF	ON	ON							
5 Pulse / zloty 10	ON	OFF	OFF							
10 Pulse / zloty 10	ON	OFF	ON							
20 Pulse / zloty 10	ON	ON	OFF							
100 Pulse / zloty 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept zloty 10						ON				
Reject zloty 10						OFF				
★ Accept zloty 20							ON			
Reject zloty 20							OFF			
★ Accept zloty 50								ON		
Reject zloty 50								OFF		
★ Accept zloty 100									ON	
Reject zloty 100									OFF	
★ Accept zloty 200										ON
Reject zloty 200										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.
(2) Dip switches 1 to 5 are only used for pulse protocol.

P77-PLN5(Pulse/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
MDB Interface		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.
(2) Dip switches 1 & 3 are only used for pulse protocol.

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON		
★ MDB Interface		OFF		
Reserved			ON	
★ Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	zloty 10	zloty 10
BV2	zloty 20	zloty 20
BV3	zloty 50	zloty 50
BV4	zloty 100	zloty 100
BV5	zloty 200	zloty 200