

A6/V6-TTD6

A6/V6 Option Switch Settings: 1(Pulse/ICT002)

Supported bill TT\$ 1, 5, 10, 20, 50, 100 6 bills.

A6/V6 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject TT\$ 1	ON											
★ Accept TT\$ 1	OFF											
★ Reject TT\$ 5		ON										
★ Accept TT\$ 5		OFF										
★ Reject TT\$ 10 & 20			ON									
★ Accept TT\$ 10 & 20			OFF									
★ Reject TT\$ 50				ON								
★ Accept TT\$ 50				OFF								
★ Reject TT\$ 100					ON							
★ Accept TT\$ 100					OFF							
★ High Acceptance	(Note.3)				ON							
★ High Security					OFF							
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / TT\$ 1								OFF	OFF			
★ 2 pulse / TT\$ 1								ON	OFF			
★ 4 pulse / TT\$ 1								OFF	ON			
★ 20 pulse / TT\$ 1								ON	ON			
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Increase accepting rate will reduce its security level. Use this option carefully!

A6/V6-TTD6(Pulse/ICT002)

A6 Interface Settings: 2(Pulse/ICT002)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
ICT002 Interface		OFF		
★ Reserved			ON	
★ Reserved			OFF	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ ICT002 Interface		OFF		
★ Reserved			ON	
★ Reserved			OFF	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

V6 Interface Settings: 2(M.D.B)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2	OFF			
Scaling Factor (SF) = 1				
Decimal Point Position (DPP) = 0				
★ Reserved		ON		
★ M.D.B Interface		OFF		
★ Reserved			ON	
★ Reserved			OFF	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	TT\$ 1	TT\$ 1
BV2	TT\$ 5	TT\$ 5
BV3	TT\$ 10	TT\$ 10
BV4	TT\$ 20	TT\$ 20
BV5	TT\$ 100	TT\$ 100
BV6	TT\$ 50	TT\$ 50

Currency Assign Data

Interface Bill value	MDB
BV1	TT\$ 1
BV2	TT\$ 5
BV3	TT\$ 10
BV4	TT\$ 20
BV5	TT\$ 100
BV6	TT\$ 50