

V6 Option Switch Settings: 1 (ICT)

Supported bill \$A 5, 10, 20, 50, 100 5bills.

V6 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject \$A 5	ON											
★	Accept \$A 5	OFF											
	Reject \$A 10		ON										
★	Accept \$A 10		OFF										
	Reject \$A 20			ON									
★	Accept \$A 20			OFF									
	Reject \$A 50				ON								
★	Accept \$A 50				OFF								
	Reject \$A 100					ON							
★	Accept \$A 100					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Reserved							ON					
★	Reserved							OFF					
	Reserved								ON				
★	Reserved								OFF				
	Reserved									ON			
★	Reserved									OFF			
	Reserved										ON		
★	Reserved										OFF		
	Reserved											ON	
★	Reserved											OFF	

★ Manufacture setting

Note : Reset the bill acceptor after setting the dip switch.

V6 Interface Settings: 2 (ICT)

INTERFACE	SW1	SW2	SW3	SW4	
★ Reserved	ON				
	OFF				
★ Reserved		ON			
★ ICT Interface		OFF			
★ Reserved			ON		
			OFF		
					ON
					OFF

★ Manufacture setting