

V6T Option Switch Settings

Supported bill MXP 20, 50, 100, 200

USD 1, 5, 10, 20 8bills.

V6T dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject MXP 20 & USD 1	ON											
★	Accept MXP 20 & USD 1	OFF											
	Reject MXP 50 & USD 5		ON										
★	Accept MXP 50 & USD 5		OFF										
	Reject MXP 100 & USD 10			ON									
★	Accept MXP 100 & USD 10			OFF									
	Reject MXP 200 & USD 20				ON								
★	Accept MXP 200 & USD 20				OFF								
	Accept Mexico Pesos and US Dollars (Note 1)					ON							
★	Accept Mexico Pesos Only (Note 1)					OFF							
	High Acceptance						ON						
★	High Security						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / MXP 10									OFF	OFF		
	2 pulse / MXP 10									ON	OFF		
	5 pulse / MXP 10									OFF	ON		
	10 pulse / MXP 10									ON	ON		
★	Interface Timing Conversion	50ms on / 50ms off										OFF	OFF
		60ms on / 300ms off										ON	OFF
		30ms on / 50ms off										OFF	ON
		150ms on / 150ms off										ON	ON

◆ Factory configuration has all switches in the OFF position.

Note : (1) For Accepting US Dollars, make sure you have dip 5 set to ON position.

(Exchange rate on USD to MXP is 1:10)

(2) Reset the bill acceptor after setting the dip switch.

(3) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V6T Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
★					ON
★					OFF

★ Manufacture setting

V6T Interface Settings: 3(MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
★					ON
★					OFF

★ Manufacture setting