

V7-AMD4

V7 Option Switch Settings: 1 (Pulse/ICT004/MDB)

Supported bill DRAMS 1000, 2000, 5000, 10000 4bills.

V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject DRAMS 1000(New)	ON											
★	Accept DRAMS 1000(New)	OFF											
	Reject DRAMS 2000		ON										
★	Accept DRAMS 2000		OFF										
	Reject DRAMS 5000			ON									
★	Accept DRAMS 5000			OFF									
	Reject DRAMS 10000				ON								
★	Accept DRAMS 10000				OFF								
	Reject DRAMS 1000(Old)				ON								
★	Accept DRAMS 1000(Old)				OFF								
	Push Out Stacker Enable				ON								
★	Push Out Stacker Disable				OFF								
	Harness Disable				ON								
★	Harness Enable				OFF								
	Inhibit Active High				ON								
★	Inhibit Active Low				OFF								
★	1 pulse / DRAMS 1000								OFF	OFF			
	2 pulses / DRAMS 1000								ON	OFF			
	4 pulses / DRAMS 1000								OFF	ON			
	20 pulses / DRAMS 1000								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)

V7-AMD4(Pulse/ICT004/MDB)

V7 Interface Settings: 3 (ICT004)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
★	Reserved	OFF			
	Pulse Mode		ON	OFF	
	MDB Interface		OFF	OFF	
★	ICT004 Interface		OFF	ON	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

V7 Interface Settings: 3 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	MDB Interface		OFF	OFF	
	ICT004 Interface		OFF	ON	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

V7 Interface Settings: 3 (MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
★	MDB Interface		OFF	OFF	
	ICT004 Interface		OFF	ON	
	Credit divided by 10				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT004	Pulse	MDB
BV1	DRAMS 1000(New)	DRAMS 1000(New)	DRAMS 1000(New)
BV2	DRAMS 2000	DRAMS 2000	DRAMS 2000
BV3	DRAMS 5000	DRAMS 5000	DRAMS 5000
BV4	DRAMS 10000	DRAMS 10000	DRAMS 10000
BV5	DRAMS 1000(Old)	DRAMS 1000(Old)	DRAMS 1000(Old)