

V77E-KZT6

V77E Option Switch Settings: 1(Pulse/ICT104U/MDB)

Supported bill KZT 200, 500, 1000, 2000, 5000, 10000 6bills.

V77E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject KZT 200 & 500	ON											
★	Accept KZT 200 & 500	OFF											
	Reject KZT 1000		ON										
★	Accept KZT 1000		OFF										
★	Reject KZT 2000			ON									
★	Accept KZT 2000			OFF									
★	Reject KZT 5000				ON								
★	Accept KZT 5000				OFF								
★	Reject KZT 10000					ON							
★	Accept KZT 10000					OFF							
	Reserved					ON							
★	Reserved					OFF							
	Pulse Mode	Other Mode											
	Harness Disable	BA stops working when fishing					ON						
★	Harness Enable	Normal					OFF						
	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
★	1 pulse / KZT 100						OFF	OFF					
	2 pulses / KZT 100						ON	OFF					
	5 pulses / KZT 100						OFF	ON					
	20 pulses / KZT 100						ON	ON					
★	Pulse Speed	50ms LO / 50ms HI							OFF	OFF			
		60ms LO / 300ms HI							ON	OFF			
		30ms LO / 50ms HI							OFF	ON			
		150ms LO / 150ms HI							ON	ON			

★ Manufacture setting

Note : (1) Default setting.

(2) Use both 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

V77E-KZT6(Pulse/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	MDB
BV1	KZT 200	KZT 200	KZT 200
BV2	KZT 500	KZT 500	KZT 500
BV3	KZT 1000	KZT 1000	KZT 1000
BV4	KZT 2000	KZT 2000	KZT 2000
BV5	KZT 5000	KZT 5000	KZT 5000
BV6	KZT10000	KZT10000	KZT10000