

NK77-LAK5

NK77 DIP SWITCHES SETTING : (Pulse/Out of Service/ICT104U)

Supported bill LAK 5000, 10000, 20000, 50000, 100000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10		
★	1 Pulse / LAK 5000	OFF	OFF										
	2 Pulses / LAK 5000	OFF	ON										
	5 Pulses / LAK 5000	ON	OFF										
	10 Pulses / LAK 5000	ON	ON										
★	Enable Fish Stop			ON									
	Disable Fish Stop			OFF									
★	Inhibit level Active Low				ON								
	Inhibit level Active High				OFF								
★	Accept LAK 5000					ON							
	Reject LAK 5000					OFF							
★	Accept LAK 10000 & 20000					ON							
	Reject LAK 10000 & 20000					OFF							
	Enable Output Sensor Detect							ON					
★	Disable Output Sensor Detect							OFF					
★	Pulse Normal High								ON				
	Pulse Normal Low								OFF				
★	Pulse Mode									ON			
	ICT104U Mode									OFF			
★	Accept LAK 50000 & 100000										ON		
	Reject LAK 50000 & 100000										OFF		

(★) Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

- (2) Pulse mode has out of service function.
(3) Out of service: Normal High, Error Low.
(4) Pulse speed is LO=50ms/HI=100ms

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	LAK 5000	LAK 5000
BV2	LAK 10000	LAK 10000
BV3	LAK 20000	LAK 20000
BV4	LAK 50000	LAK 50000
BV5	LAK 100000	LAK 100000